



FHM2 Series Optical Multimeter

- Integrated laser source and optical power meter
- Dual or triple wavelength output
- Suitable for fiber or device insertion loss test
- Up to 999 test results storage
- With LCD backlight function and auto power off

Model	Specifications			
	FHM2A01	FHM2A02	FHM2B01	FHM2B02
Laser Source Part (LD)				
Output Wavelength	1310/1550nm	1310/1490/1550nm	1310/1550nm	1310/1490/1550nm
Output Power	-5dBm(Typical)	0dBm(Typical)	-5dBm(Typical)	0dBm(Typical)
Frequency Output	270Hz/1kHz/2kHz			
Power Meter Part (PD)				
Test Range	-70~+10dBm		-50~+26dBm	
Resolution	0.01dB			
Calibrated Wavelength	850/1300/1310/1490/1550/1625nm			
Accuracy	±0.2dB			
Frequency Detection	270Hz/1kHz/2kHz			
Wavelength Detection	Support			
Memory Capacity	999 groups			
Others				
Communication Port	USB Type-C			
Optical Port	FC/UPC or SC/UPC			
Power Supply	2* Ni-MH AA battery Input: AC100~240V, 50/60Hz Output: DC5V/1A			
Working Temp	-10°C~+50°C			
Storage Temp	-20°C~+70°C			
Dimension/Weight	160L×76W×45H(mm) / 310g			



歲望有限公司

802626 高雄市苓雅區新光路38號5樓之1
電話：07-5368282 傳真：07-5368272

WEVANT Co., Ltd.

5F.-1, No.38, Xinguang Rd., Lingya Dist.,
Kaohsiung City 802, Taiwan (R.O.C.)
TEL: +886-7-5368282 FAX: +886-7-5368272



Let's go in the grandway!